

# CM-2030

## AC Clamp Meter(1000 Ampere)

**HTC**<sup>TM</sup>  
**INSTRUMENTS**

### Features:

- 3 1/2 MANUAL AC CLAMP METER.
- FULLY PROTECTED in the RANGE
- CLAMP OPEN: 52mm.
- Clamp Torch.



### Technical data:

Function	Range	Resolution	Accuracy
DC VOLTAGE (DCV)	1000V	1V	±(0.8%+2)
AC VOLTAGE (ACV)	750V	1V	±(1.0%+5)
AC Current (ACA)	200A	0.1A	±(3.0%+5)
	1000A	1A	
Resistance (Ω)	200 Ω	0.1 Ω	±(1.0%+3)
	20k Ω	10 Ω	
	200k Ω	100 Ω	
Diode and Continuity	Description	Test Condition	
	Diode forward voltage drop.	Forward DC Current is approx 1mA, Reserve DC voltage is less than 3V.	
	When resistance is less then 30±10 Ω, buzzer sounds	Open circuit voltage is about 3V	

- **Standard Accessories** : Soft Carrying case, Manual, Probe
- **Dimension** : 123(H) x270(W) x 35(D)mm

