



❖ **DIGITAL PORTABLE WATT / VAR / POWER FACTOR METERS**



"MECO-G" Portable Digital Watt meters can measure power in single phase systems with Unity Power factor (P.F=1.0) and Low Power Factor (P.F=0.2). These instruments are more rugged, reliable and accurate than analog meters. They are light in weight, compact in size and stylish in design. They do not have any moving parts. Display is bright Red LED's. There is no confusion of anti-parallax scale.

WATT / VAR METERS (4 ½ and 3 ½ DIGIT DISPLAY)

	R-PDW11	R-PDW11L	R-PDV11
MODEL:	SINGLE PHASE UNITY P.F WATTMETER (4 ½ Digit).	SINGLE PHASE LOW P.F WATTMETER (3 ½ Digit).	SINGLE PHASE VAR METERS (4 ½ Digit).

	RANGES	ACCURACY	RESOLUTION
VOLTS	0-75, 100, 125, 150, 250, 300, 500, 600V (any one)	± 0.5% of Full Scale	1 Watts
CURRENT	0-0.5, 1, 1.5, 2, 2.5, 5, 10A (any one)		

	R-PFM11P	R-PFM31P
MODEL:	SINGLE PHASE (Single Element Power Factor Meter)	THREE PHASE (Single Element Power Factor Meter)

	RANGES	ACCURACY
VOLTS	0-110V / 220V / 440V (any one)	± (0.3%Rdg. + 4dgt)
CURRENT	0-1A / 5A (any one)	

DIMENSIONS:
(All dimensions in mm)

